

WINDING TURNS TESTER

VE201R



Brief Introduction :

Winding Turns Tester is one of our best products with reliable quality, high measurement speed, high accuracy, excellent performance and easy to use. It can measure Turns / Polarity and DC Resistance of any Air core Coil, motor windings, high / low voltage coil transformers, Relay coil and so on. It is widely used for production, R&D or Q.C.

Main Functions :

- Microprocessor Based Instrument
- 4 Terminal Measurement / Kelvin Measurement for measuring Resistance
- Good Measurement Stability and Performance
- Does not require a Standard Coil when every you test

Specification :

Max. Size of Coil	I.D > 4mm ; O.D < 120 mm ; H < 110 mm
Turns Range	0 ~ 80,000 Turns
Turns Accuracy	0 ~ 1000 T (± 0.2% ± 1 Turn) 1001 ~ 20,000 T (± 0.3% ± 2 Turn) > 20,000 T (± 0.5% ± 8 Turn)
Resistance Range	100 mOhm ~ 20 KOhm
Resistance Accuracy	± 0.5% ± 1 dgt
Display Mode	6 digit LED display
Range Mode	Auto Range
Alarm Setup	Short, Phase and Silent Selectable
Power Requirement	110V ~ 240 V AC (47Hz ~ 63Hz)
Dimension	335mm X 320mm X 290mm
Weight	Approx 6 KG

VASAVI ELECTRONICS

95, Road No.6A, Jyothi Colony, SECUNDERABAD - 500 015, (T.S), INDIA

Tel : +91 - 40 - 27744445 ; Web : www.vasavi.co.in / www.vasavi.com ; E-mail : vasavielectronics@gmail.com